

DisplayPort to Dual DP/HDMI Multi Monitor Adapter



Item no. FS12106

Specification:

- Connector 1: DisplayPort 1.2 male
- Connector 2: DisplayPort 1.2 female/HDMI 2.0 female
- Gold plated contact, Gold plated shell
- Cable Conductor: Tinned Copper
- Insulation: Foamed PE SKIN/HDPE
- Wire Gauge: 32AWG
- Shielding: Aluminum Foil, Braiding
- Housing: Aluminum Shell
- Jacket: PVC
- Outer diameter: 4.8 ± 0.2 mm
- 4K@60Hz for single port, 4K@30Hz for dual port
- Support MST(only windows), SST
- Compliance: RoHS, REACH

Order Informaiton:

- FS12106A: DisplayPort to Dual DP Multi Monitor Adapter, 0.2M
- FS12106B: DisplayPort to Dual HDMI Multi Monitor Adapter, 0.2M

Description:

Let's talk about the FARSINCE DisplayPort to Dual DP/HDMI Female Adapter with micro USB charge.

This handy gadget is a must-have for anyone serious about their home theater or desktop setup.

It's perfect for streaming or gaming, supporting SST and MST, with 4K@60Hz for a single port and 4K@30Hz for dual ports. The audio transmission is flawless too, delivering uncompressed digital 7.1, 5.1, or 2 channels.

The built-in IC chip enhances compatibility, making it an indispensable tool for transferring audio and video signals from your computer to your monitor.

If you're ready to take your viewing and gaming experience to the next level, this adapter is a solid bet!

Note: It is not a bi-directional adapter cable, can only convert signal from DisplayPort to Displayport/HDMI